## **SPS-Series**

## Switching DC Power Supply SPS-4128A

15~25Amp power supply The SPS-series DC power supplies was designed

specifically for use with land mobile radio, and it produce clean reliable power and is highly filtered to suppress RFI.

## Application

- Communications equipment
- Automobile sound & display systems
- Testing of DC equipment and appliances
- Portable entertainment equipment and appliance
- Vehicle accessories and DC lighting systems
- Security systems and CCTV
- Toys and hobbies
- Cooler boxes



## Feature

- Short circuit and over voltage protection
- Output power rated at continuous service
- Binding post output terminals
- Input voltage can be set at 120VAC or 240VAC
- Complies with CE standards
- Low peak-peak ripple of less than 1%
- High surge capacity
- Heavy duty metal cabinet with powder coated

| Specification |                            |                  |                |       |                |            |
|---------------|----------------------------|------------------|----------------|-------|----------------|------------|
| Model         | Input                      | Output           | Output Current |       | Dimensions     | Net Weight |
| Number        | Voltage                    | Voltage          | Continuous     | Surge | L x W x H (mm) | Kg         |
| SPS-4128A     | 110 ~ 220VAC<br>Switchable | 13.8VDC<br>Fixed | 15Amp          | 25Amp | 182 x 220 x 72 | 1.8        |